

# Photoelectric Smoke Sensor

VF2011-00



## Ordering Codes

VF2011-00	Photoelectric Smoke Detector
VF7001-00	4" Mounting Base
VF7002-00	6" Mounting Base
VF7008-00	6" Sounder Base
VF7005-00	6" Low Frequency Sounder Base

## Standard Features

- Low Profile - Only 2" high, including base
- Simple and reliable device addressing
- Automatic compensation for sensor contamination
- Built-in fire test feature
- Uses the noise-immune Digital Communication Protocol (DCP), which utilizes interrupts for fast response to fires
- Two built-in power/alarm LEDs
- Programmable non-polling LEDs
- Non-directional smoke chamber
- Vandal resistant security locking feature
- Removable smoke labyrinth for cleaning or replacement

**NOTE** Bases are not included with detectors, please order separately.

## Operation

The detection chamber consists of a light-emitting diode (LED) and photodiode arrangement. The chamber is designed such that light emitted by the LED cannot normally reach the photodiode. In the event of fire, particles of smoke enter the chamber and scatter the light. As the smoke level increases, the scattering effect increases, causing more light to hit the photodiode. The chamber contains a unique baffle design which allows smoke to enter the chamber while preventing external light from affecting the photodiode. The photodiode input level is sampled to sense smoke density.

When the smoke density exceeds a preset threshold the sensor transmits an interrupt to the fire control panel indicating a fire condition. The fire alarm control panel can adjust the sensor threshold to compensate for contamination.

Up to 127 devices are permitted on each SLC loop. A sensor address is set by a hand-held programming unit. The sensor mounts to an electronics-free base and incorporates a locking mechanism for secure installation. The base provides mounting slots, terminals for field wiring and a third contact for a remote indicator/LED. The sensor incorporates dual LEDs for easy viewing of sensor status.



## Application

The VF2011 Photoelectric Smoke Sensor is particularly suited to detecting optically dense smoke typical of fires involving materials such as soft furnishings, plastic, foam or other similar materials which tend to smoulder and produce large visible smoke particles. VES's unique design allows fast response to flaming fires as well as smoldering fires while preventing false alarms.

## Engineering Specification

The contractor shall furnish and install where indicated on the plans, photoelectric sensors VES Model VF2005. The combination sensor head and twist lock base shall be UL listed compatible with a UL listed fire alarm control panel. The Sensor and Base shall be UL listed as compatible with the fire alarm control panel (FACP).

The sensitivity of the sensor shall be capable of being measured by the control panel.

The vandal-resistant, security locking feature shall be used in those areas as indicated on the drawing. The locking feature shall be optional and can be implemented when required.

## Bases

The VF7001 and the VF7002 mounting bases are electronics free and are a simple rugged design with screw terminals for wiring connections. A common mounting base allows sensor interchange and maintains loop continuity when sensors are removed. A simple anti-tamper head locking system is provided which is enabled by removing a small plastic tab on the back of the sensor. Once locked, the head can be removed using a small diameter screw driver.

## Technical Specifications

Operating Voltage	24 - 41 VDC
Standby Current	450 $\mu$ A
Alarm Current	540 $\mu$ A
Transmission Method	DCP—Digital Communication Protocol
Maximum Humidity	up to 95% non-condensing
UL Temperature Range	32° F to 120° F
Sensitivity Range	0.7 - 4.0% / FT @ 300 FPM 0.7 - 3.86% / FT @ 2000 FPM 0.7 - 2.65% / FT @ 4000 FPM
Air Velocity Range	0-4000 fpm
Color and Case Material	Bone / White - ABS Blend
Weight	3.4 oz, (5.1 oz with 4" base)